

ADC-V622

SPECIFICATIONS

RECORDING COMPRESSION

H.264

IMAGE SENSOR

1/2.9" CMOS, 6.8 MP, 3096 x 2202

LENS / ANGLE OF VIEW

1.62 mm, F2.3, 180°

LOW-LIGHT SENSITIVITY

0 lux with IR

IR RANGE

Up to -15 feet (5 m)

IMAGE ADJUSTMENTS

Flip, brightness, contrast, saturation, sharpness, exposure

WIRELESS CONNECTIVITY

802.11 b/g/n, 2.4 & 5 GHz

OPERATING TEMPERATURE

32°F - 104°F (0°C - 40°C)

OPERATING HUMIDITY

20% - 80% (non-condensing) RH

MAX POWER CONSUMPTION

12V DC, 12W

DIMENSIONS (L x W x H)

3.125 x 3.125 x 5.2" (7.9 x 7.9 x 13.2 cm)

REQUIREMENTS

POWER

Power over Ethernet or 12V DC power adapter (included)

NETWORK

Wi-Fi (2.4 or 5 GHz) or ethernet connection to broadband Internet



180° HD Camera with Enhanced Zoom and Two-Way Audio

Equipped with speakers, a microphone, and advanced video and audio features, the ADC-V622 is a wide-angle camera with a full 180° field of view. A 6 MP image sensor and digital pan, tilt, and enhanced zoom capabilities give users true high definition video even when viewing zoomed-in live feeds. With a clean, modern design, the camera also features a call-out button. One tap initiates a Two-Way Audio call with other users on the account via the Alarm.com app. The ADC-V622 uses echo cancellation to block unwanted noise for a seamless conversation experience. With Bluetooth-enabled speakers, customers can also use the camera to stream music from any mobile device.

FEATURES

- Wide-angle 180° field of view
- Digital pan / tilt / zoom
- Built-in Bluetooth speaker
- Two-Way Audio with push to call
- Power over Ethernet or Wi-Fi (2.4GHz or 5GHz)
- Works with the Alarm.com customer website and mobile app

INCLUDED ACCESSORIES

- Power Adapter
- Quick Installation Guide
- Mounting Hardware

LED GUIDE

	LED STATUS	DESCRIPTION
STATUS LED 	Off	Power off
	Flashing Red	Power on, camera booting
	Flashing Green	Local network connection
	Solid Green	Connected to Alarm.com
	Blinking Blue	WPS mode
	Blinking White	Wi-Fi Access Point mode
TROUBLE CONDITION	Solid Red	No local or Internet connection
FACTORY RESET	Alternating Red and Green	Camera resetting to factory default